## B1277 ProTalk Cv3

## Highlights

- Class 1 Div 2 Rating for hazardous areas
- Flexible inputs can accept discrete contacts, analog voltage or analog current (4-20 mA)
- Extreme temperature rating of -40°C to +60°C
- Receive Alarm Summary and Health Status Reports via Email or SMS text
- Low power mode for solar panel applications

## **Specifications**

Enclosure	Steel, powder coated matte black			
Environment	Mounting ears for panel installation $40^{\circ}$ C to $\pm 60^{\circ}$ C $05^{\circ}$ / humidity pan condensing			
Connectors	-40°C to +60°C, 95% humidity, non-condensing			
Power	Plug-in screw terminal block unless noted			
FOWEI	+9 to +30 VDC, negative ground, 1.0A Max.			
	Internally fused at 1.85A			
	Optional internal rechargeable 1.4Ahr 12 volt			
Alarma Innuita (10)	battery backup			
Alarm Inputs (10)	Alarm Inputs (10) All inputs will withstand up to +30 VDC <u>Digital mode</u> - Inputs 1-10:			
	Internal 4.7k ohm pull-up resistor to +5 VI			
	Operate with ground closure Low state threshold of +2 VDC Trips when open or closed			
	Analog voltage mode - Inputs 1-10:			
	-	0k ohm (inputs 1-6)		
		k ohm (inputs 7-10)		
	<b>J</b>	to +5 or 0 to +30 VDC		
	Analog current mode - Inputs 7-10:			
	•	0 ohm between pins		
		K ohm to ground		
		to 20mA		
Relay Outputs (4)	2 contact terminals per relay, programmable as			
	normally open or normally closed			
	Contact Rating: 2A at 30VDC			
	Latching relays - no continuous power re			
Radio Port	RX audio & TX audio: 600 ohms, single ended,			
	capacitor coupled, 0 dBm to -20 dBm			
Program Ports	USB: USB type B connector			
	Telset: RJ11 connector, accepts standard			
	touch-tone telephones			
Shutdown Switch	Momentary pushbutton			
Rating	CSA/UL Safety Approvals inc. Class I, Div. 2			
SIM	2FF/mni SIM card			








## Available Accessories

PN	Description	
INT BATT	1.4AH 12VDC Internal battery backup	
B1258	15V 24W AC/DC adapter	
NEMA	NEMA 4X Environmental enclosure	
ANT DB WIDEBAND	Wideband antenna; for poor coverage areas	
ANT OMNI	Omnidirectional antenna; for good coverage areas	
ANT DB PHANTOM	Bulkhead mount phantom antenna	
LP COAX	Coax lightning protector 700-2200MHz	

Dimensions			
Length (L) cm (in)	Width (W) cm (in)	Height (H) cm (in)	<b>Weight</b> kg (lb)
25.40 (10)	7.62 (3)	13.97 (5.5)	1.13 (2.5)



www.barnettprotalk.com